

Western Electric Co., Incorporated,  
Engineering Dept.,  
New York.

(2 Pages) Page #1.  
Issue 1 - BT-431753.  
October 5, 1920.

METHOD OF OPERATION  
OVERFLOW REGISTER CIRCUIT.

Permanent Signal Trunk Group - Sender Monitor Operator - Trouble Desk - Full  
Mechanical Power Driven System.

GENERAL DESCRIPTION

1. This circuit is used at the trouble desk to light a lamp at the sender monitoring position as an indication that the district selector has gone to the overflow terminals of a permanent signal trunk group. It is common to the overflow terminals of the permanent signal trunk groups of all district frames.

DETAILED DESCRIPTION

OPERATION

2. When a district selector connects to the terminals of this circuit and advances, ground is temporarily connected to battery through lead T, and the windings of the L relay and 5-P message register in series which operate. The L relay operated, locks to ground on its armature and closes a circuit from ground on its armature to battery, through the winding of the OF relay, 2-G lamp and relay in the associated auxiliary signal circuit operating the relays and lighting the lamp under control of the NL key.

3. The 5-P message register operated, short circuits the winding of the L relay which releases.

4. When the non-locking key associated with the lighted lamp at the sender monitoring position is operated, the lamp is extinguished and the OF relay releases restoring the circuit to normal.

(2 Pages) Page #2.  
Issue 1 - BT-451753.  
October 5, 1920.

CIRCUIT REQUIREMENTS

	<u>OPERATE</u>	<u>NON-OPERATE</u>	<u>RELEASE</u>
Special A 7-10541 (L)	Test .036 amp. Readj. .034 amp.	Test .026 amp. Readj. .028 amp.	
B10 (OF)	Test .045 amp. Readj. .025 amp.		Test .0038 amp. Readj. .004 amp.
5-P Message Register	Test .070 amp.	Test .060 amp.	

ENG.--HBH-VL.  
7-22-22.

CHK'D.--CAL.

APPROVED - C. L. SLUYTER, C.M.L.